

FEATURE UPDATE | AUGUST 2025

Version 253 Update

Updated Version 253 (8/22/25) firmware is now available for XR Series Control Panels.

OSDP Support

This update allows XR Series Control Panels to receive and send OSDP commands to [7873 Series Touchscreen Keypads with firmware Version 209 \(8/22/25\)](#) and [734 Access Control Modules firmware Version 108](#).

New reader LED actions can be configured in [Entré Version 9.8.2 \(9/4/25\)](#).

To use the OSDP commands for the 734 at the keypad, 734 Access Control Modules with firmware Version 108 is required. The following programming fields display at the keypad:

1. At the keypad, enter **6653** (PROG) and select **CMD** to enter the programming menu.
2. Go to **DEVICE SETUP**.
3. At **PROGRAM 734 OPTIONS?**, select **YES**.
4. At **READER PROTOCOL**, select **OSDP**. The options below only display if you select **OSDP**.
5. AT **OSDP PASSPHRASE**, enter a secure passphrase up to 16 alphanumeric characters that is used to establish encrypted two-way communication between the reader and module.
6. At **LED CONTROL**, select **YES** to enable reader LED operation. Select **NO** to leave this option disabled.
7. At **BUZZER CONTROL**, select **YES** to enable reader annunciation. Select **NO** to leave this option disabled.
8. At **TAMPER CONTROL**, select **YES** to enable tamper control. Select **NO** to leave this option disabled.

Obtaining the New Firmware

XR Series firmware updates are available, free of charge, on Dealer Admin (dealer.securecomwireless.com) or for download from DMP's [Product Software Downloads](#).