

Version 255 Update

Updated Version 255 (12/30/25) firmware is now available for XT75 Control Panels.

Remote OSDP Support

This update allows XT75 Control Panels to receive and send OSDP commands to [7873 Series Touchscreen Keypads with firmware Version 209 \(8/22/25\)](#) and [734 Access Control Modules with firmware Version 108 \(6/15/25\)](#).

All new reader LED actions can be configured on [Dealer Admin](#).

To use this update, 734 Access Control Modules with firmware Version 108 (6/15/25) is required. To program OSDP commands at the keypad, complete the following steps:

1. At the keypad, enter **6653** (PROG) and select **CMD** to enter the programming menu.
2. Go to **DEVICE SETUP**.
3. At **PROGRAM 734 OPTIONS?**, select **YES**.
4. At **READER PROTOCOL**, select **OSDP**. The options below only display if you select **OSDP**.
5. AT **OSDP PASSPHRASE**, enter a secure passphrase up to 16 alphanumeric characters that is used to establish encrypted two-way communication between the reader and module.
6. At **LED CONTROL**, select **YES** to enable reader LED operation. Select **NO** to leave this option disabled.
7. At **BUZZER CONTROL**, select **YES** to enable reader annunciation. Select **NO** to leave this option disabled.
8. At **TAMPER CONTROL**, select **YES** to enable tamper control. Select **NO** to leave this option disabled.

Wireless Tamper Notifications

XT75 Control Panels now send notifications on Dealer Admin and Virtual Keypad for wireless tampers.

2G Fallback

This update supports the ability to switch back to 2G cellular network.

TCP Trapping Support

XT75 now supports TCP Trapping in Remote Link. For more information, refer to the [TCP Trapping Application Note](#).

Network Connection

Previously, if the XT75 was unable to obtain an IP address from the DHCP server after a prolonged time, the panel stopped trying to reconnect to network. Now, the panel continues to attempt reconnection until network is restored.

Obtaining the New Firmware

XT75 firmware updates are available, free of charge, on Dealer Admin (dealer.securecomwireless.com) or for download from DMP's [Product Firmware Downloads](#).